

## ENCODER COUPLINGS

The flexible joint mounted on the encoder shaft grants a very good coupling, without parallel and angular mis-alignment, and avoids overloads, which can damage the bushings life.

Type	Specifications				
Code	Material	Torque with/without inverion	Max.offset of the shaft angular/parallel	Dimensions $\emptyset$ x Length.mm	Hole d1/d2 mm
<b>BSS06-06</b> BSS0606	Aluminium	2.6 / 1.3 Nm	7° / 0.25 mm	19.05 x 20	6 / 6
<b>WA 8-8</b> WA8-8	Aluminium	0.95 / 0.475 Nm	5° / 0.25 mm	22.22 x 25.4	8 / 8
<b>WA 10-10</b> WA10-10	Aluminium	1.1 / 0.55 Nm	5° / 0.25 mm	25 x 24	10 / 10
<b>SK 4-4</b> SK4-4	Polyamid fiberglass reinforced Aluminium insertion	0.20 / 0.10 Nm	2.5° / 0.25 mm	15 x 20	4 / 4
<b>SK 6-6</b> SK6-6		0.80 / 0.40 Nm	3° / 0.25 mm	22 x 24	6 / 6
<b>SK 8 - 8</b> SK8-8		0.80 / 0.40 Nm	3° / 0.25 mm	22 x 24	8 / 8
<b>SK 10-10</b> SK10-10		0.80 / 0.40 Nm	3° / 0.25 mm	22 x 24	10 / 10

